Update the standard FreshBrew service HMI-board

Important information before getting started
Make sure to have both the software update file and the settings file on a empty USB.

The update and settings file can be downloaded from the website ***www.bravilor.com***, through the dealer login.

- 002.071.052 software HMI
- 002.112.xxx recipes and settings, ***this depends on the type***.
  FG100 - 002.112.001
  FG121 - 002.112.002
  FG143 - 002.112.003
  FM100 - 002.112.004
  FM121 - 002.112.005

► *Don't unzip these files, they need to be on the USB as a zip file.*
The machine will extract the files automatically during the update.

► *As the **settings file** is machine-dependent, please ensure that you have downloaded the correct one*

Procedure for updating the service HMI-board:

► *Make sure that the service HMI-board is installed correctly on the machine.*

- turn the machine on
- the machine will retrieve data from the power board in the machine to see which type of machine it is
  - type number
  - serial number
  - machine model
  - life time counter
    * *if data can't be retrieved from the power board it can be manually entered*
    * *make 100% sure to provide the machine with the correct data*
- add the USB with the software update to the inside of the door
- select the ***software HMI*** *'002.071.052'*
- press the *'install button'* on the screen
- the update process can take several minutes, please wait
  a message appears on the screen that the update is installed
- press the *'restart button'*
  during the restart the machine will apply the software update and the screen can show different colors around the display (this may take a few minutes)
- the machine will now start-up,
  some settings such as *language*, *date* and *time* need to be added manually
- the machine will then ask for the ***settings file*** *'002.112.xxx'*
- press the *'import settings button'* (this takes about twenty seconds)
- restart is required, press the *'restart button'*
- the machine will now start up in the first installation program and, once this has finished, it will be ready to be used